

5. CONFIGURE DEVICE SETTINGS

By selecting a device and clicking the device settings button



you will be taken to the device settings management screen. From there you will be able to remotely view and/or configure the settings for each NovoPRO device on your network.

Novo-BAABB42FC (192.168.50.187)

General Network Sleep Timer Security Signage Misc.

Device Name Design Lab < Apply

Model NovoConnect-NC-X700

Edition Corporate

App Version v4.1.0.54 Online Update

Build Version NovoConnect-NC-X700-0054

Software Edition X700-EU-CORP-EDU

Online Users 0

Refresh Close

Customize Home-screen Background

Some NovoConnect devices allows users to customize its background pictures of the home-screen. To do so for NovoPro, click tab “Misc.”

1. Then a configuration dialog pops up, with two sections, “Preload” and “User-defined.”
 - a. Section “Preload”: the built-in content. It has two video clips and 3 pictures. You can enable/disable their playback as well as adjust their playback duration.
 - b. Section “User-defined”: the customization content. Users can edit the “playlist” for this slideshow

area. The “playlist” consists of any numbers of pictures and videos.

Home Screen Config - jack (192.168.8.106)

Preload

☐ Video 1: Product Introduction

☐ Video 2: Setup Guide

☐ Picture 1: Overview

Duration: 10 seconds

☐ Picture 2: First time using NovoPRO

Duration: 10 seconds

☐ Picture 3: Joining the meeting

Duration: 10 seconds

User-defined

+ Add

File	Name	Duration
	slide_1.png	10
	slide_1.png	10
	slide_1.png	10
	slide_1.png	10

Sync

Go Back

Cancel

1. Click on button “Sync” to commit the changes to the NovoPRO device (including uploading the content.)

<

Back